



## IP Camera Installation and Setup Guide

XLE NVR MODELS

## Adding and Configuring IP Cameras

You should add and configure the online IP cameras to enable the live view and recording function.

### Adding IP Cameras

You can search and add the online IP cameras by following the startup wizard, or according to the following steps.

1. Enter the Camera Management interface.
  - a) Click on Menu.
  - b) Click on Camera.
  - c) Click on Camera.



2. To add the online cameras with same network segment:
  - a) Click on **Search** to search the online cameras.



Camera Settings Interface

- b) Click on the **Check box** of the cameras to be added.
  - c) Click **Quick Add** to add the cameras.
  - 3. To add other IP cameras:
    - d) On the left side of the interface, you can enter the IP address, protocol, management port, and other information of the IP camera to be added.
    - e) Click **Add** to add the camera.
- Note:** If you check the Synchronize IP Camera check box, the default settings of the NVR for the IP camera is applied to the added camera.

### Configuring Basic Parameters of IP Cameras

After the adding of the IP cameras, the basic information of the camera lists in the page, and you can configure the basic setting of the IP cameras.

1. Click the  icon to edit the parameters; you can edit the IP address, protocol and other parameters.

**Edit IP Camera**

IP Camera No.	D1
IP Camera Address	172.6.16.115
Protocol	Custom 1 <span style="float: right;">▼</span>
Manage Port	0
Channel No.	1 <span style="float: right;">▼</span>
User Name	user
Admin Password	

2
3

Apply
OK
Cancel

Edit the Parameters

2. Click on **Apply** to save the setting
3. Click on **OK** to exit the editing interface.

## Advanced Parameters

To edit more parameters:

1. Click the **Advance Set** icon.

Advance Set	
Network	Password
IP Camera No.	D3
IP Camera Address	172.6.21.116
Manage Port	8000

Apply    OK    Cancel

Network Configuration of the Camera

2. You can edit the network information and the password of the camera.
3. Click on **Apply** to save the settings.
4. Click on **OK** to exit the interface.

